

## Digital Manometers

### Introduction

With all microprocessor electronics, these stylish and rugged digital manometers measure differential pressures of clean gases. FM models are approved and intrinsically safe for hazardous locations.

### Specifications

	<b>475 Series</b>	<b>PM80</b>
Construction:	Extruded Aluminium	IP67 ABS
Accuracy:	0.5% at 23°C	0.2% at 23°C
Ranges:	249Pa to 10.34 bar	0/130 mBar
Functions:	On/Off, Zero, Units	On/Off, Zero, Hold, Unit
Battery:	9v PP3	9v PP3 Life 200 hours



Dwyer 475 Series



PM-80

### Features

- Easy to read display
- Easy grip ABS case (PM80)
- Rugged Aluminium Case (Dwyer)
- Intrinsic Safe Options
- Multiple engineering units as standard

### Models Available

Order Code	Mfr Code	English Range	Metric Range
IPM-DPM80	PM-80	0-2.00 psi	0-13.00 kPa
IPM-D475*000	475-000	0-1.000 in wc	0-.2491 kPa
IPM-D475*00FM	475-00-FM	0-4.000 in wc	0-0.996 kPa
IPM-D475*0FM	475-0-FM	0-10.00 in wc	0-2.491 kPa
IPM-D475*1FM	475-1-FM	0-20.00 in wc	0-4.982 kPa
IPM-D475*2FM	475-2-FM	0-40.00 in wc	0-9.96 kPa
IPM-D475*3FM	475-3-FM	0-200.0 in wc	0-49.82 kPa
IPM-D475*4FM	475-4-FM	0-10.00 psi	0-.6895 bar
IPM-D475*5FM	475-5-FM	0.20.00 psi	0-1.379 bar
IPM-D475*6FM	475-6-FM	0-30.00 psi	0-2.069 bar
IPM-D475*7FM	475-7-FM	0-100.0 psi	0-6.895 bar
IPM-D475*8FM	475-8-FM	0-150.0 psi	0-10.34 bar

**Postal Address**  
Homersham Ltd  
PO Box 280  
Christchurch 8140  
NEW ZEALAND

Phone: 03 3588309  
Phone: 0800 659888

Website: [www.homershams.co.nz](http://www.homershams.co.nz)

**Delivery Address**  
Homersham Ltd  
3 Homersham Place  
Burnside  
Christchurch 8053  
NEW ZEALAND

Fax: 03 3582516  
Fax: 0800 659777

E-mail: [info@homershams.co.nz](mailto:info@homershams.co.nz)

132

